



**1610 - DAILY OPERATOR CHECKLIST**

**PRE-OPERATION CHECKLIST**

- Vacuum floor and remove any debris
- Check battery meter charge level indication
- ReadySpace Cleaning: Check rollers for wear
- Restorative Extraction Cleaning: Check the brushes for wear
- Inspect spray nozzles for proper spray pattern
- ReadySpace Cleaning: Inspect roller vacuum shoes for debris
- Restorative Extraction Cleaning: Inspect the extraction shoe for debris
- Make sure the recovery tank float shut-off screen is clean
- ReadySpace Cleaning: Make sure solution tank is filled with only water, no cleaning detergents
- Restorative Extraction Cleaning: Fill the solution tank with recommended cleaning detergent and water

**POST-OPERATIONAL CHECKLIST**

- Drain and rinse out the recovery and solution tanks after every use
- Rinse out the recovery tank and the float shut-off screen with clean water
- Rotate the ReadySpace rollers end-for-end every 10 hours of use
- Remove any debris build-up from the underside of the scrub head
- Remove the front and rear roller vacuum shoe covers and remove any debris
- Remove any entangled carpet fibers and debris from the brushes
- Remove any debris lodged in the restorative extraction vacuum shoe
- Inspect the spray tips for proper spray pattern
- Clean the machine housing with an all purpose cleaner and damp cloth
- ReadySpace Cleaning: Remove the splashguard cover and inspect the rollers for wear. If the gap between the two rollers is greater than 4mm (5/32") replace the rollers. Always replace rollers as a set.
- Check battery charge level and charge the batteries as required  
 Before charging the batteries, check the electrolyte level in each battery cell
  - *To prolong the battery life, ONLY recharge the batteries after a total of 30 minutes of use or more.*

List below any problems that occurred during operation.

\_\_\_\_\_

\_\_\_\_\_

**OPERATOR** \_\_\_\_\_

**DATE** \_\_\_\_\_

**SUPERVISOR** \_\_\_\_\_

**DATE** \_\_\_\_\_

<sup>1</sup> E:\TECHTR\MACHINES\1610\1610OPCK.DOC